Up-date to the service manual Studer A816


UP-DATE Tape De	ck Section 6	
	Main Transformer 300VA	1.816.520.81
	Stabilizer	
	MP-Unit TD Control	1.816.785.24
	Capstan Motor Drive Amplifier PCB	1.820.774.27
	Tacho Sensor Electronics	1.021.695.86
UP-DATE Master	Section 7	
	MP Unit Master	1.816.786.24
UP-DATE		
Description of the section of the se	Bandabhebeaggregat, Andruckmechanik	Seite 9/13
	9.6 Andruckaggregat	Seite 9/14
UP-DATE Zubehö	r Section 10	
	Tape Deck Remote Control Cabinet (Parallel)	1.328.250.81
	- Tape Deck Remote Control PCB	1.328.251.81

Tape Deck Remote Control Cabinet (Parallel)	. 1.328.250.81
- Tape Deck Remote Control PCB	. 1.328.251.81
Tape Deck Remote Control Module (Parallel)	. 1.328.255.81
- Connector PCB	
Remote Timer/Lap Mode Display	. 1.328.270.00
- Stabilizer PCB	. 1.328.213.81
Remote Control Cabinet (Serial)	. 1.328.210.81
Remote Control Module (Serial)	. 1.328.220.81
- Stabilizer PCB	
- Remote Control Driver PCB	. 1.328.211.25
Autolocator Module	. 1.328.230.82
Autolocator Cabinet	
- Stabilizer Board	. 1.328.213.81


Prepared and edited by: STUDER Professional Audio AG **Technical Documentation** Althardstrasse 30 CH-8105 Regensdorf - Switzerland STUDER is a registered trade mark of STUDER Professional Audio AG, Regensdorf


Copyright by STUDER Professional Audio AG Printed in Switzerland Order no. 10.27.3820 (Ed. 0895)


We reserve the right to make alterations



MAINS TRANSFORMER 300 VA 1.816.520.81











STABILIZER 1.811.790.81






STABILIZER 1.811.790.81






STABILIZER 1.811.790.81

STABILIZER 1.	11.790.01	and Columbia
AdPOSREF.No.	DESCRIPT	IONMANUFACTURER
R16 57.11.31 R17 57.11.33		1½ 5½
R17 57.11.33 R18 57.11.31 R19 57.11.31 R20 57.11.32	.03 10 k0hm .03 10 k0hm	56 56 18 58
R21 57.11.31 R22 57.11.34	54 150 kOhm	5% 1%
R23 57.11.31 R24 57.11.37	32 1.3 kOhm 52 7.5 kOhm	14 14 54
R25 57.11.32 R26 57.11.33 R27 57.11.32 R28 57.11.32	20 22 Ohm	5% 5% 5%
R29 57.11.38 R30 57.11.31	22 8.2 k0hm	5% 5%
R31 57.11.34 R32 57.11.32 R33 57.11.31	22 2.2 kOhm	5% 1% 5%
R34 57.11.32 R35 57.11.32 R36 57.11.32	79 2.7 Ohm 22 2.2 kOhm	5% 1% 5%
R37 57.11.31 R38 57.11.31 R39 57.11.32	02 1 k0hm 03 10 k0hm	14 54 14
R40 57.11.31 R41 57.11.36	33 13 kOhm	14 54
R42 57.11.31 R43 57.11.34 R44 57.11.31	02 1 k0hm 73 47 k0hm	5% 5%
R45 57.11.34 R46 57.11.31	70 47 Ohm 03 10 kOhm	54 54 55 54
R47 57.11.33 R48 57.11.32 R49 57.11.31 R50 57.11.31	54 150 kOhm	5% 5% 1%
R51 57.11.34 R52 57.11.32	73 47 kOhm	14 54
R53 57.11.33 R54 57.11.31 R55 57.11.31	32 3.3 kOhm 03 10 kOhm	55 15 14
R56 57.11.32 R57 57.11.32 R58 57.11.32	20 22 Ohm 20 22 Ohm	\$\frac{9}{9}\$ \$\frac{9}{9}\$ \$\frac{9}{9}\$ \$\frac{9}{9}\$ \$\frac{9}{9}\$ \$\frac{9}{9}\$
R59 57.11.32 R60 57.11.31	22 2.2 kOhm	5% 5% 5%
R61 57.11.32 R62 57.56.20		5% 3%, 3W
RA2 58.05.15 RA2 58.05.15	01 500 Ohm 01 500 Ohm	10%, multi turn 10%, multi turn
T1 1.022.629. T2 1.022.627.	00 00	Switching Transformer St Switching Transformer St
TP1 54.02.03		Test Point
/!\ = Increasing of safe Note 1 - Connector:	ety relative to	risk of fire.
10 contacts, Note 2 - Connector:	AMP Nr.	826 852-3
case,	Studer Nr. Molex Nr. Studer Nr.	54.02.0409 03-06-1121 54.02.0407
Note 3 - Connector:	Molex Nr.	02-06-7103
case,	Studer Nr. Molex Nr. Studer Nr.	54.02.0408 03-06-2121 54.02.0406
	Molex Nr.	02-06-8103
MPC=Metallized Polycarb	onate film.	instruments, IPS=Integrated Power
Semi condu Mot=Motore	ctor, ITT=Interm ola, NS=National	etall, IR=International Rectifier, Semiconductors, Ph=Philips,
General, S St=Studer	Sie=Siemens, Sig	Sescosem, SGS-SGS/Ates, SG-Silicon =Signatics, Six=Siliconix, Tho=Thomson, Ti=Texas Instruments,
	B1 STABILIZER	GP 95/03/2200




MP-UNIT TAPE DECK CONTROL 1.816.785.24






CAPSTAN MOTOR DRIVE AMPLIFIER PCB 1.820.774.27






CAPSTAN MOTOR DRIVE AMPLIFIER PCB 1.820.774.27







TACHO SENSOR ELECTRONICS PCB 1.021.695.86




TACHO SENSOR ELECTRONICS PCB 1.021.695.86







MP-UNIT MASTER 1.816.786.24





UP-DATE

Bandabhebeaggregat, Andruckmechanik

Pos.	Menge	Bestell-Nr.	Bezeichnung Spezifikation
1	1	1.014.732.00	Abhebemagnet
2	1	1.014.731.00	Andruckmagnet
3	1	1.816.130.00	Bandabhebeaggregat
3.1	1	1.816.131.00	Bandabheberolle komplett
3.2	1	1.862.120.07	Gelenkstück
4	1	1.816.132.00	Zugstange zu Abhebemagnet, kompl.
5	1	1.816.142.00	Anker mit Gelenkstück
5.1	1 1	1.816.140.05	Gewindestange zu Andruckmagnet
5.2	1 1	1.862.120.07	Gelenkstück
5.3	1	1.010.219.37	Andruckfeder
6	1	1.816.090.34	Gewindestange zu Edithebel
7	1	1.816.134.08	Drehknopf (EDIT)

UP-DATE STUDER A816






Andruckaggregat

Pos.	Menge	Bestell-Nr.	Bezeichnung S	pezifikation
1	1	1.816.140.00	Andruckaggregat kompl.	
1.1	1 1	1.010.036.21	Senkschraube spezial	M4 x 14
1.2	1 1	1.816.090.45	Rollendeckel	
1.3	1	1.816.138.00	Andruckrolle	
1.4	1	1.816.141.04	Andruckrollen-Achse	
1.5	1	1.816.141.03	Achsenhalter, einstellbar	
1.6	1	21.51.8455	Linsenschraube	M4 x 8
1.7	1 1	1.816.141.05	Sechskantbolzen spezial	
1.8	1 1	1.010.104.37	Feder	D5 / 13,6
1.9	3	21.53.0457	Z-Schraube mit Sicherungsscheibe	e M4 x 12
1.10	1 1	1.862.120.07	Bronzehebel	
1.11	1	22.01.8040	Mutter	M4/0,8 D
1.12	1 1	23.01.1040	Rippenscheibe	zu M4
1.13	1 1	23.01.1043	Unterlagsscheibe	D 4,3/8,0
1.14	1	1.816.140.03	Sechskantbolzen spezial	
1.15	1	24.16.3032	Benzing-Sicherungsscheibe	D 3,2

TAPE DECK REMOTE CONTROL CABINET (PARALLEL) 1.328.250.81

- Tape Deck Remote Control PCB 1.328.251.81






TAPE DECK REMOTE CONTROL CABINET (PARALLEL) 1.328.250.81



- Tape Deck Remote Control PCB 1.328.251.81 Ad ..POS.. ...REF.No... DESCRIPTION..... .MANUFACTURER 31.01.0103 DL..201 DL..202 DL..203 DL..204 not used MW5353 CM4-584B. HLMP-3401 CM,GI,HP 50.04.2112 not used MW5353 CM,GI,HP CM4-584B. HLMP-3401 50.04.2112 50.05.0283 50.05.0279 NS,Tho,TI LM393N SG3524BN 53.03.0166 53.03.0168 1.328.252-00 JS....1 L.....1 1.022.197.00 Anschlüsse miteinander ● D17 verdrillt flach aufgelegt 00000000000000 und verlötet zur P...100 54.01.0269 Kupferfläche. P...101 54.01.0227 R 22 P...200 54.01.0269 3 cont. AMP Nr. 163.740-1 28.31.0006 P...201 54.01.0227 35.03.0109 BC327-25 ITT, Ph, Sie 50.03.0351 35 03 0120 Q.....1 330 Ohm Verschlüsse oben 57.11.3331 57.11.3331 57.11.3331 57.11.3331 57.11.3331 57.11.3331 57.11.3331 (C40) + (C20)4 (Befestigungslöcher Print und Lötöse konzentrisch.) P201 R20 (T) H 2 02 (202) ★JS1 POS L = LIFTER 57.11.3223 57.11.3222 57.11.3122 57.11.3105 57.11.3105 57.11.3302 57.11.3222 57.11.3222 57.11.3101 57.11.3109 POS B = BACKSPACE \$ 10 S 7 8.8 S 6 Α 1.328 251-11 1810.735-12 57.11.3122 57.11.3101 57.11.3472 57.11.3472 57.11.3472 57.11.3102 57.11.3101 57.11.3101 57.11.3105 **** R104 ● 21 • 22 S 3 S 2 В 26 R...100 57.11.3151 150 Ohm 57.11.3151 57.11.3151 57.11.3151 57.11.3151 150 Ohm 150 Ohm 150 Ohm 150 Ohm R...200 57.11.3151 150 Ohm R...201 R...202 R...203 R...204 57.11.3151 57.11.3151 57.11.3151 57.11.3151 Ad ..POS.. ...REF.No... DESCRIPTION.MANUFACTURER 20%, 16V, Sal 5%, PETP 1%, Pp 10%, PETP 20%, 6.3V, Sal 20%, PETP -10%, 40V, El 35V/us 59.26.2100 59.06.5102 59.06.1103 59.06.0223 59.26.0680 59.06.0683 59.22.6100 59.03.2104 10 uF 1 nF 10 nF 22 nF 68 uF 68 nF 10 uF 1 nF Ansicht A+B 1N4448 1N4448 1N4448 1N4448 1N4448 1N4448 1N4448 1N4448 1N4448 A nur 2 DL und 2 Draht-Note 1 - Contact pin: Studer 54.01.0020, Berg 75 160-102-36 Bridge: Studer 54.01.0021, Philips 2422 024 88003 brücken bestückt. Yamaichi FAP-26-08//4, Burndy BPH 9 B 26 BOO GS Note 2 - Connector: Studer 55.03.0261, Rafi 3.13001.110 Studer 55.03.0262, Rafi 5.55101.690 Ce=Ceramic, El=Electrolytic, Sal=Solid aluminium, PETP=Polyesterfilm, Pp=Polypropylen. Fc,ITT,Ph,Ses,Tf Fc,ITT,Ph,Ses,Tf Fc,ITT,Ph,Ses,Tf Fc,ITT,Ph,Ses,Tf Fc,ITT,Ph,Ses,Tf FC,ITT,Ph,Ses,Tf PD 6.2 ITT,Ses Mot 0....11 0....12 0....13 0....14 0....15 0....16 0....17 50.04.0125 MANUFACTURER: CMcNicogo Ministur, Ferfirchild.
Glosmoral Instruments, Mo-Membatt Packard,
ITT-intermetall, Mot-Motorola,
NS-National Semi conductors, Ph-Philips, Ses-Sescosem,
SG-Silicon General, Sies-Siemens, St-Studer, Tho-Thomson,
IT-lexas Instruments, IT-felefunken. 50.04.0125 50.04.0125 50.04.0125 50.04.1118 BZX83C 6.2, BZX55C 6.2, ZPD 6.2 1N5819 26.1.94 24 4 4 Datum Gez Ges Gos In-CM4-584B, HLMP-3401 CM4-584B, HLMP-3401 CM4-584B, HLMP-3401 CM4-584B, HLMP-3401 DL..100 DL..101 DL..102 DL..103 DL..104 50.04.2112 MW5353 MW5353 MW5353 1.328.251.81 TAPE DECK REMOTE CONTROL ML 94/01/2600 50.04.2112 TAPE DECK REMOTE CONTROL BOARD ESE 50.04.2111 CM4-284B, HLMP-3301 1.328.251-81 DL..200 not used

TAPE DECK REMOTE CONTROL MODULE (PARALLEL) 1.328.255.81






TAPE DECK REMOTE CONTROL MODULE (PARALLEL) 1.328.255.81




- Connector PCB 1.328.257.81



REMOTE TIMER / LAP MODE DISPLAY 1.328.270.00

- Stabilizer PCB 1.328.213.81






0 24 10.85 CHE	O	O	0		0
	A820/A812				PAGE 1 OF 1
STUDER	STABILIZER	BOARD		sc ,	1.328.213.81

REMOTE TIMER / LAP MODE DISPLAY 1.328.270.00


Stabilizer PCB 1.328.213.81



REMOTE CONTROL CABINET (SERIAL) 1.328.210.81 REMOTE CONTROL MODULE (SERIAL) 1.328.220.81

- Stabilizer PCB 1.328.213.81






① 24 .10 .85 CHE	0	O	0		0
	A820/A812				PAGE 1 OF 1
STUDER:	STABILIZER	BOARD		SC /	1.328.213.81

REMOTE CONTROL CABINET (SERIAL) 1.328.210.81 REMOTE CONTROL MODULE (SERIAL) 1.328.220.81

- Stabilizer PCB 1.328.213.81






REMOTE CONTROL CABINET (SERIAL) 1.328.210.81 REMOTE CONTROL MODULE (SERIAL) 1.328.220.81




- Remote Control Driver PCB 1.328.211.25



REMOTE CONTROL CABINET (SERIAL) 1.328.210.81 REMOTE CONTROL MODULE (SERIAL) 1.328.220.81




- Remote Control Driver PCB 1.328.211.25



AUTOLOCATOR MODULE 1.328.230.82 AUTOLOCATOR CABINET 1.328.240.82

- Stabilizer Board 1.328.213.81





0 24.10.85 CHE	0	O	0		0
	A820/A812				PAGE 1 OF 1
STUDER	STABILIZER	BOARD		SC A	1.328.213.81

AUTOLOCATOR MODULE 1.328.230.82 AUTOLOCATOR CABINET 1.328.240.82

Stabilizer Board 1.328.213.81



